

---

# Power Optimizer

## For North America

P801 / P850 / P950 / P1100



POWER OPTIMIZER

### PV power optimization at the module-level

The most cost-effective solution for commercial and large field installations

- Specifically designed to work with SolarEdge inverters
- Up to 25% more energy
- Superior efficiency (99.5%)
- Balance of System cost reduction; 50% less cables, fuses and combiner boxes, over 2x longer string lengths possible
- Fast installation with a single bolt
- Advanced maintenance with module-level monitoring
- Module-level voltage shutdown for installer and firefighter safety
- Use with two PV modules connected in series or in parallel

# / Power Optimizer For North America

P801 / P850 / P950 / P1100

Power Optimizer Model (Typical Module Compatibility)	P801 (for up to 2 x 72-cell PV modules)	P850 (for up to 2 x high power or bi-facial modules)	P950 (for up to 2 x high power or bi-facial modules)	P1100 (for up to 2 x high power or bi-facial modules)			
<b>INPUT</b>							
Rated Input DC Power <sup>(1)</sup>	800	850	950	1100	W		
Connection Method	Single input for series connected modules						
Absolute Maximum Input Voltage (Voc at lowest temperature)	125				Vdc		
MPPT Operating Range	12.5 - 105				Vdc		
Maximum Short Circuit Current per input (Isc)	11.75	14.1*		14.1	Adc		
Maximum Efficiency	99.5				%		
Weighted Efficiency	98.6				%		
Overvoltage Category	II						
<b>OUTPUT DURING OPERATION (POWER OPTIMIZER CONNECTED TO OPERATING SOLAREEDGE INVERTER)</b>							
Maximum Output Current	15	18			Adc		
Maximum Output Voltage	80				Vdc		
<b>OUTPUT DURING STANDBY (POWER OPTIMIZER DISCONNECTED FROM SOLAREEDGE INVERTER OR SOLAREEDGE INVERTER OFF)</b>							
Safety Output Voltage per Power Optimizer	1 ± 0.1				Vdc		
<b>STANDARD COMPLIANCE</b>							
Photovoltaic Rapid Shutdown System	NEC 2014						
EMC	FCC Part 15 Class A, IEC61000-6-2, IEC61000-6-3						
Safety	IEC62109-1 (class II safety), UL1741						
Material	UL94 V-0, UV Resistant						
RoHS	Yes						
<b>INSTALLATION SPECIFICATIONS</b>							
Compatible SolarEdge Inverters	SE9K & larger		SE20K & larger		SE30K & larger		
Maximum Allowed System Voltage	1000					Vdc	
Dimensions (W x L x H)	129 x 153 x 49.5 / 5.1 x 6 x 1.9		129 x 162 x 59 / 5.1 x 6.4 x 2.3			mm / in	
Weight	933 / 2.05		1064 / 2.34			gr / lb	
Input Connector	MC4 <sup>(2)</sup>						
Input Wire Length	0.16 / 0.52	1.3 / 4.27	0.16 / 0.52	1.6 / 5.24	1.3 / 4.27	1.6 / 5.24	m / ft
Output Wire Length	2.2 / 7.2		2.1 / 6.9	2.2 / 7.2	2.2 / 7.2	2.4 / 7.8	m / ft
Output Wire Type / Connector	Double Insulated / MC4						
Operating Temperature Range <sup>(3)</sup>	-40 to +85 / -40 to +185					°C / °F	
Protection Rating	IP68 / NEMA6P						
Relative Humidity	0 - 100					%	

\* For P850/P950 models manufactured in work week 06/2020 or earlier, the maximum Isc per input is 12.5A. The manufacture code is indicated in the Power Optimizer's serial number  
example: S/N SJ0620A-xxxxxxx (work week 06 in 2020)

(1) Rated power of the module at STC will not exceed the Power Optimizer "Rated Input DC Power". Modules with up to +5% power tolerance are allowed

(2) For other connector types please refer to: <https://www.solaredge.com/sites/default/files/optimizer-input-connector-compatibility.pdf>

(3) For ambient temperature above +70°C / +158°F power de-rating is applied. Refer to <https://www.solaredge.com/sites/default/files/se-temperature-derating-note-na.pdf> for more

PV System Design Using a SolarEdge Inverter <sup>(4)(5)(6)</sup>		208V Grid SE14.4K*		208V Grid SE17.3K*		277/480V Grid SE20K, SE30K, SE33.3K*, SE40K*	277/480V Grid SE20K, SE30K	277/480V Grid SE33.3K*, SE40K*	
Compatible Power Optimizers		P801	P850, P950, P1100	P801	P850, P950, P1100	P801	P850, P950, P1100	P850, P950, P1100	
Minimum String Length	Power Optimizers	8	8	9	9	14	14	14	
	PV Modules	15	15	17	17	27	27	27	
Maximum String Length	Power Optimizers	30	30	30	30	30	30	30	
	PV Modules	60	60	60	60	60	60	60	
Maximum Continuous Power per String		6000	7200	7275	8730	12750	15300	15300	W
Maximum Allowed Connected Power per String <sup>(7)</sup> (Permitted only when the difference in connected power between strings is up to 2,000W for the 277/480V grid, or 1,000W for the 208V grid)		2 strings or less - 7200 3 strings or more - 7800	1 string - 8400	2 strings or less - 8475 3 strings or more - 9075	1 string - 9930 2 strings or more - 10530	15000	1 string 17550 2 strings or more - 20300	2 strings or less - 17550 3 strings or more - 20300	W
Parallel Strings of Different Lengths or Orientations		Yes							

\* The same rules apply for Synergy units of equivalent power ratings, that are part of the modular Synergy Technology inverter

(4) P850/P950/P1100 can be mixed in one string only with P850/P950/P1100. P801 cannot be mixed with any other Power Optimizer in the same string

(5) For each string, a Power Optimizer may be connected to a single PV module if 1) each Power Optimizer is connected to a single PV module or 2) it is the only Power Optimizer connected to a single PV module in the string

(6) Design with three phase 208V inverters is limited. Use the [SolarEdge Designer](#) for verification

(7) To connect more STC power per string, design your project using [SolarEdge Designer](#)